


# **SLC64LWIR cooled 640×512 Infrared Imaging Module**

## **TECHNICAL DATA**

***V1.0***



# CONTENT

<b>1. Brief Introduction .....</b>	<b>1</b>
<b>2. Declarations .....</b>	<b>2</b>
<b>3. Features .....</b>	<b>3</b>
3.1. Image Output Gating .....	3
3.2. Internal-sync and External-sync Output .....	4
3.3. NUC and Dead Pixels Replacement .....	4
3.4. Spatial Filtering .....	4
3.5. Display Modification on Image Output .....	4
3.6. Image Orientation .....	4
3.7. Brightness and Contrast Adjustment .....	5
3.8. Digital Detail Enhancement (DDE) .....	5
3.9. Image Contrast Enhancement .....	5
<b>4. Electrical Interfaces .....</b>	<b>5</b>
4.1. Connector Definition .....	5
4.2. Camera Link Output Protocol .....	6
4.3. RS422 Protocol .....	8
4.4. SDI Video Output .....	8
4.5. External Sync Interface .....	8
<b>5. Command Words .....</b>	<b>8</b>
<b>6. Dimensions .....</b>	<b>9</b>

## 1. Brief Introduction

This standard type of Cooled Infrared Imaging Module is based on the 640×512 LW Cooled Infrared Detector and compatible with most similar types of IR detectors. It can transform the infrared radiation into visualized image. Rich functionalities and interfaces, compact size and low power consumption make it easy to use for the system integration and secondary development. It is utilized in various applications on the security & surveillance, border patrol, UAV load and R&D.

### The Module Includes,

➤ Cooled LW Infrared Detector	1 each
➤ DB Board	1 pc
➤ AD Board	1 pc
➤ Detector Interface A Board	1 pc
➤ Detector Interface B Board	1 pc
➤ Cooler Driving Board	1 pc
➤ Power Supply Board	1 pc
➤ Internal Connection Cables	1 set

### The main features and specifications are as below,

- Sensitive Material: T2SL
- Image Resolution: 640×512
- Spectral Range: 7.7(±0.2)μm ~10.5(±0.2)μm
- Pitch Size: 15um
- F number: 2
- NETD: ≤ 25mK or Detector Typical NETD+5mK
- Max Frame Rate of Image Output: 50/100 Hz
- Video Output Interfaces: Camera Link and SDI (digital), others can be customized
- Image Output Type: 8-bit or 14-bit electable

- Power Consumption:  $\leq 20\text{W}$  (steady-state),  $\leq 30\text{W}$  (during cooling down)
- Cooling Down Time:  $\leq 8$  min (room temperature)
- Image Polarity: White Hot/ Black Hot
- Digital Detail Enhancement
- Image Contrast Enhancement
- Image Filtering and De-noising
- Image Integration: Auto/manual Modification on the integration time
- Internal Sync or External Sync
- Single and Two-point NUC, the correction parameters can be fixed
- Auto/Manual Dead pixels replacement
- Provides test images, such as gray level gradient, stripe target and checkerboard
- Analog image rollover, mirroring, freeze and digital zooming
- Crosshair overlay/remove
- Operating Temperature:  $-40\sim+60^{\circ}\text{C}$
- Storage Temperature:  $-55\sim+70^{\circ}\text{C}$
- Humidity:  $0\%\sim 80\%\text{RH}$

## **Interfaces and Power Supply**

- Digital Video Output: CameraLink@14bit, CameraLink@8bit.
- SDI Video Output: 1080P@50Hz, 1080P@25Hz or 720P@50Hz;  
effective display resolution  $640\times 512$ .
- Communication Interface: RS422
- External Sync: Differential LVDS or RS422
- Power Supply: 24V DC (nominal), 18~36V DC

## **2. Declarations**

- The module cannot be used with the power supply out of the defined voltage range.
- Any disassembly on the electronic boards without permission breaks the maintenance terms and conditions.
- Except the analog output, any hot-plugging on another connectors is prohibited.

- This documents is only related to the electronic boards and the imaging module. For further detailed information of the cooler, please refers to the cooler operation manual or contact the cooler manufacture.

### 3. Features


#### 3.1. Image Output Gating

The module provides the feature of online gating on the real-time IR image and test images. Users can select the image output among 14-bit, 16-bit, 8-bit gray scale, and test images. The analog and digital video interfaces are changed synchronously with the image output gating. This feature is also customizable.


There are 9 types of test images, including row gray level and its dynamic map, column gray level and its dynamic map, row 5-square target and its dynamic map, column 5-square target and its dynamic map, and also checkerboard.



Row gray level



Column gray level



Checkerboard

Fig 3-1 Examples of test images

### **3.2. Internal-sync and External-sync Output**

The module provides the feature of internal-sync and external-sync output, which can be switched automatically or manually. When the module is working under the external-sync mode, the image will be output at the corresponding frame rate if the external-sync signal is detected. If not, the module will switch to internal-sync mode automatically. The frame rate of the external-sync signal is less than the maximum frame rate of the image output.

### **3.3. NUC and Dead Pixels Replacement**

The module provides the feature of single and two-point Non-uniformity correction and dead pixels replacement. The default image is output after NUC and dead pixels replacement. If users change the infrared lens, the NUC should be executed again on the module together with the new lens. The correction parameters should also be saved accordingly.

### **3.4. Image Spatial Filtering**

The module provides the feature of image spatial filtering. Users can open or close that filtering and modify the filtering coefficient. The smaller coefficient, the stronger filtering effect. This feature is default enabled. Generally, the module works properly under the default mode and relative parameters.

### **3.5. Display Modification on Image Output**

The module provides the feature of display modification on image output. The image can be displayed at White hot or Black hot mode.

### **3.6. Image Orientation**

The module provides the feature of image orientation adjustment. The image can be output with Mirror Horizontally or Mirror Vertically.

### 3.7. Brightness and Contrast Adjustment

The brightness and contrast of the image can be adjusted online.

### 3.8. Digital Detail Enhancement (DDE)

The module provides DDE feature. Users can adjust the image through the DDE level. The higher DDE level, the stronger enhancement effect.

### 3.9. Image Contrast Enhancement (ICE)

The module provides the feature of image contrast enhancement. Users can adjust the image contrast through the ICE level. The higher ICE level, the stronger enhancement effect.

## 4. Electrical Interfaces

### 4.1. Connector Definition

The connector definition and wiring instruction are as below,

1) type name: J30J-25ZKP, matching connector: J30J-25TJL. The definition as below,

Pin	Signal	Connecting pin/signal	Remark
1	P_I_24V+	Connecting with system	Power supply+, voltage range 18V~36V
14	P_I_24V+		
2	GND		Power supply -
15	GND		
3	RS422 TXD+		IR RS422 Output
16	RS422TXD-		
4	RS422RXD+		IR RS422 Input
17	RS422RXD-		
5	DGND		Digital GND
6	CMD2_CLKOUT+		Camera Link CLK
18	CMD2_CLKOUT-		
7	CMD2_OUT0+		Camera Link Channel 0
19	CMD2_OUT0-		

Pin	Signal	Connecting pin/signal	Remark
8	CMD2_OUT1+		Camera Link Channel 1
20	CMD2_OUT1-		
9	CMD2_OUT2+		Camera Link Channel 2
21	CMD2_OUT2-		
10	CMD2_OUT3+		Camera Link Channel 3
22	CMD2_OUT3-		
23	DGND		Digital GND
11	NC		
24	NC		
12	Sync+		External-sync, differential LVDS or RS422
25	Sync-		
13	NC		

2) SDI video connector: PP4, Type name: MCX\_KWHD. The definition as below,

Pin	Signal	Connecting Pin/signal	Remark
1	SDI		Signal
2、3、4、5	AGND		GND

#### 4.2. Camera Link Output Protocol

Camera Link Output is developed with TI DS90CR285MTD/NOPB. The 14-bit or 16-bit digital image is transferred according to the 16-bit×1 wiring definition of Base0 basic configuration refer to the Camera Link Standard 2.0. The wiring definition is as below. The data is from Camera\_Data0 to Camera\_Data15. Camera\_LVAL is for effective row signal, Camera\_FVAL is for effective frame signal, Camera\_DVAL is for effective data signal and Camera\_CLK is for pixel CLK signal.




Fig 4-1 Camera Link Wiring Definition

As below, CLK=Camera\_CLK, FVAL=Camera\_FVAL, LVAL=Camera\_LVAL, DVAL=Camera\_DVAL, DATA=Camera\_Data[0-13]. N is for effective pixel value of 1 frame, CLK is for pixel CLK, DATA is 512 rows and the first row is in front. The data of each row has 640 pixels. The data aligns to the top edge of CLK.




Fig 4-2 Camera Link Timing

### **4.3. RS422 Protocol**

The module can be controlled through RS422 interface. The RS422 is in accordance with below information. The default RS422 setup is,

**Baud Rate 115200, 8bits data, 1 start bit, 1 stop bit, even parity bit.**

### **4.4. SDI Video Output**

The default output resolution of SDI video is 720P, with the effective display area being the 640×512 area in the center of the screen, while the remaining part is filled with a black background.

### **4.5. External-sync Interface**

The external-sync interface is LVDS differential level.

## **5. Command Words**

The module is controlled through RS422 interface. It doesn't send out any information, but only receives the information from the outside host machine. When receiving the command words in accordance with the protocol, the module executes the command and feedbacks the results.

The communication command words are also customizable.

## 6. Dimensions





Fig 6-1 Dimensions of 640x512 detector






Fig 6-2 Dimensions of 640×512 IR imaging module